

ASE ComCenter II Series













The **ASE ComCenter II Series** brings your Iridium Satellite link indoors to provide low-cost, low-maintenance, secure access to remote networks and equipment anywhere in the world.

A choice of enhanced voice and data features lets you select the ComCenter II model that optimizes your satellite communications application!

FEATURES

ENHANCED VOICE

- RJ-11 (POTS) for PABX or wireless base station
- Intelligent Privacy Handset

SMS TEXTING

- Embedded ASE SatChat
- Intelligent Privacy Handset

ENHANCED DATA

- IP Port Forwarding for machine-tomachine (M2M) Apps and VSAT Diagnostics
- e-mail, weather info, Blogs

APPLICATIONS

- Maritime Communications
- Corporate Resilience
- Emergency Back-Up Communications
- VSAT Back Door Diagnostics
- GPS Reporting and Asset Tracking
- Low-Cost SMS Texting

Data transfer and real-time streaming of controls might incur additional service charges. Consult your Iridium Service Provider to determine the best plan for you.





ASE ComCenter II Series



Product Selector

| ComCenter II - Product Family | Order Number | Voice Interface (Privacy Handset) | Voice Interface (POTS/ PABX) | SMS Texting | e-mail, Weather, Blogs | M2M Port Forwarding (ethernet) | GPS |
|----------------------------------|--------------|---|---------------------------------|----------------|--|--------------------------------------|-----|
| | | | | lol:) | The first are some first and the source of t | | |
| II - 200 | ASE-MC07 | | | Χ | X | X | |
| II - 200G | ASE-MC07G | | | Χ | X | X | X |
| | | | | | | | |
| II - 300 | ASE-MC08 | X | X | Χ | X | X | |
| II - 300G | ASE-MC08G | X | X | Χ | X | X | X |

Product Detail

Included with all ComCenter Models

- Universal AC/DC Power Adapter
- Installation CD-ROM with User's Manual and Quick Start Guide
- Embedded ASE SatChat Text Messaging

Optional Accessories Include

- Privacy handset with swivel mount bracket (add -H to Order Number, example: ASE-MC08-H)
- Fixed Mount Antenna with 10m Cable (Order Number: ASE-FA01)
- 3rd Party email, Weather and Blog Application**



ComCenter II shown here with Intelligent Privacy Handset and Swivel Mount Bracket.

Specifications

Interface Cable Lengths (Max)

RJ-11 (Voice) 3,000m (9,800ft) Ethernet (Data) 120m (400ft)

Electrical Specifications

Operating Voltage 10 - 36 VDC

4 Watts (Idle/Standby) **Power Consumption** 9 Watts (Avg Active) 15 Watts (Peak)

Environmental Specifications

Operating Temp Range -30°C to +60°C Exposure Indoor, protected location

per IEC 60945

Mechanical Specifications

Dimensions (L)22.8cm x (W)12.7cm x (H)6.3cm (L)9.0in x (W)5.0in x (H)2.5in

Weight 0.9kg (2.0 lbs) Mounting Wall Mount

Iridium Antenna Requirements (Use only an Iridium approved antenna)

Cable Run must not I MR-196 6m (20ft) exceed 3db signal loss LMR-240 9m (30ft) LMR-400 18m (58ft) Max Cable Runs 27m (90ft) LMR-600 LMR-900 40m (133ft) LMR-1200 54m (176ft)

Internal GPS Specifications (G Models Only)

Tracking L1, C/A Code, AGPS, Signals Tracked SBAS, (WAAS, EGNOS)

Frequency 1575.42 MHz Channels 16 Update Rate Up to 4 Hz Report Rate Configurable

Accuracy

Horizontal Position < 2.5 m (1 - Sigma) < 2.0 m (SBAS) < 515 m/s Velocity

Altitude 10,000 m (33,000 ft) max



^{**}Service fees may apply