# **EXPLORER Cellular Modem**

Turn your BGAN into a Wireless Access Point

July 2015 Product Sheet

The most important thing we build is trust





# **EXPLORER** Cellular Modem



Turn your BGAN into a Wireless Access Point

- Custom USB LTE Dongle for the EXPLORER 510 and EXPLORER 710 BGAN terminals. Requires EXPLORER 510 Software 1.02 or later and EXPLORER 710 Software 1.06
- Simply connect the USB dongle to the USB Host port of the BGAN terminal and use a local cellular network as an alternative to BGAN
- Use your BGAN as a wireless access point for all your devices
- Requires an activated data SIM card for your local cellular provider

#### **Dimensions:** Height: 88mm Width: 28mm 11.5mm Depth: Weight: >35g 38mm **Communication System:** FDD: DD800/900/1800/2100/2600 UMTS. 900/2100 GSM: 850/900/1800/1900 Speed: LTE FDD: Cat4 DL:150Mbps/UL:50Mbps @20M BW UMTS: DCHSPA+:42/5.76Mbps;21M/5.76Mbps; 14M/5.76M HSUPA: 7.2M/5.76M 11.5mm 28mm 2GEDGE packet data service of up to 236.8kbps

## Other features:

2 TS-5 External Antenna Interfaces MicroSD card slot

### **BGAN firmware:**

EXPLORER 510 ver. 1.02 / EXPLORER 710 ver. 1.06 or later

### Product number:

403756A-00500: EXPLORER Cellular Modem

For further information please contact:

Cobham SATCOM Lundtoftegaardsvej 93 D DK-2800 Kgs. Lyngby Denmark Tel: +45 3955 8800 Fax: +45 3955 8888